

0	0	nul	1	1	soh	2	2	stx	3	3	etx	4	4	eot	5	5	enq	6	6	ack	7	
8	8	bs	9	9	ht	10	A	nl	11	B	vt	12	C	np	13	D	cr	14	E	so	15	
16	10	dle	17	11	dc1	18	12	dc2	19	13	dc3	20	14	dc4	21	15	nak	22	16	syn	23	1
24	18	can	25	19	em	26	1A	sub	27	1B	esc	28	1C	fs	29	1D	gs	30	1E	rs	31	1
32	20	sp	33	21	!	34	22	"	35	23	#	36	24	\$	37	25	%	38	26	&	39	2
40	28	(	41	29	)	42	2A	*	43	2B	+	44	2C	,	45	2D	-	46	2E	.	47	2
48	30	0	49	31	1	50	32	2	51	33	3	52	34	4	53	35	5	54	36	6	55	3
56	38	8	57	39	9	58	3A	:	59	3B	;	60	3C	<	61	3D	=	62	3E	>	63	3
64	40	@	65	41	A	66	42	B	67	43	C	68	44	D	69	45	E	70	46	F	71	4
72	48	H	73	49	I	74	4A	J	75	4B	K	76	4C	L	77	4D	M	78	4E	N	79	4
80	50	P	81	51	Q	82	52	R	83	53	S	84	54	T	85	55	U	86	56	V	87	5
88	58	X	89	59	Y	90	5A	Z	91	5B	[	92	5C	\	93	5D	]	94	5E	^	95	5
96	60	'	97	61	a	98	62	b	99	63	c	100	64	d	101	65	e	102	66	f	103	6
104	68	h	105	69	i	106	6A	j	107	6B	k	108	6C	l	109	6D	m	110	6E	n	111	6
112	70	p	113	71	q	114	72	r	115	73	s	116	74	t	117	75	u	118	76	v	119	7
120	78	x	121	79	y	122	7A	z	123	7B	{	124	7C		125	7D	}	126	7E	~	127	7

C OPERATOR ASSOCIATIVITY		Bit	IRQ	PRIORITY	A	0-127	/8	10.0.0.0	10.FF.FF.FF
→	() [] -> .	8	0	Timer	B	128-191	/16	172.16.0.0	172.31.FF.FF
←	! ~ ++ -- + - * & (type) sizeof	8	1	Keyboard	C	192-223	/24	192.168.0.0	192.168.FF.FF
→	* / %	16	8	Cascade 8-15	D	224-239	/8	↑ RFC1918	↓ Multi-.
→	+ -	16	9	RTClock	E	240-247	/?	↑ Local	↓ cast
→	≤ < ≥ > >=	16	10	[Redir → 2]	DMA			Ports 0x3FF	
→	== !=	16	11	[CD / Ether]					
→	& (Bitwise And)	16	12	[SCSI]	8	0	(Refresh)	12 to 10 bit decoding	
→	^ (Bitwise Xor)	16	13	[PS2 Mouse]	8	1	Floppy		
→	(Bitwise Or)	16	14	FloatPoint U	8	2			
→	&& (Boolean And)	16	15	Disc IDE 0	8	3		C=8=4=0** D=9=5=1** E=A=6=2** F=B=7=3**	
→	(Boolean Or)	8	3	Disc IDE 1	16	4	Cascade		
←	? :	8	4	Serial1 Com2	16	5	SCSI		
←	= += -= *= /= %= &= ^= = <<= >>=	8	5	Serial0 Com1	16	6		A: 0.0.0.0 -0.FF.FF.FF B: 169.254.0.0 -169.254.FF.FF C: 192.0.2.0 -192.0.2.FF D: 224.0.0.0 - 239.FF.FF.FF E: 240.0.0.0 - 255.FF.FF.FF	
→	, (Chapter 3 (< K&R P.49/53))	8	6	Paralel Lpt2	16	7			
		8	7	Floppy	16	6			
		8	7	Paralel Dflt	16	7			